



The GDS-1000B Series digital storage oscilloscopes equip with 200/100/70 MHz : 2 Channel models; 100/70/50 MHz : 4 Channel models, that provide entry level users with diversified selections. The maximum real time sampling rate can be up to 1GSa/s. The robust functional performance makes the economical oscilloscope more colorful and allows entry level users to sumptuously enjoy the fun and value brought by test and measurement which is precisely the emerging mission of the test and measurement industry that GW Instek works relentlessly to achieve.

10M memory depth for each channel yields exquisite measurement results and allows each retrieved waveform to successfully reveal the details of signal. Engineers are often baffled by failing to retrieve signal details when measuring basic electric circuit signals. Now, GDS-1000B series oscilloscopes, with 10M memory depth for each channel, are capable to uncover all signal details.

7" 800 x 480 WVGA LCD display and the 256 color gradient display function together allow the GDS-1000B Series to distinctly display waveform details in gradients while measuring fast changing analog signals. Additionally, 50,000wfms/s waveform update rate helps engineers clearly understand the gradients of signal variations and easily identify the problem of transient signal variations.

1Mpts FFT signal display makes the frequency domain display function more delicate. Engineers can clearly observe the distributed details of frequency domain signals. Smooth and rapid response can even better locate where the problems are originated. Powerful FFT function realizes high efficient spectrum analysis measurement which is indispensable for technology and education arenas.

The GDS-1000B series provides serial bus analysis function with 10M long memory depth. Users can trigger, decode, and analyze frequently used I²C, SPI and UART serial bus and CAN/LIN bus, which is often used by automotive communications.

The GDS-1000B Series oscilloscopes provide the zero key function for vertical voltage scale adjustment, horizontal time scale adjustment and trigger level adjustment. When processing complicate waveform adjustment and observation, engineers often require the zero key function to start a new measurement, adjust waveform or reset trigger level. The zero key function can reduce time in turning control knobs that is a great benefit for engineers.

GDS-1000B/R Series

FEATURES

- 200/100/70/50 MHz : 2 Channel models ; 100/70/50 MHz : 4 Channel models
- 1GSa/s Maximum Sampling Rate
- 10M Maximum Memory Depth For Each Channel
- 7" 800 x 480 WVGA LCD Display
- 256 Color Gradient Display Function to Strengthen Waveform Performance
- 1Mpts FFT Frequency Domain Signal Display
- I²C/SPI/UART/CAN/LIN Serial Bus Trigger and Decoding Functions
- Zero Key Function For Horizontal Time, Vertical Voltage and Triggering
- Compact and Innovative Exterior Design



Front



Rear Panel

APPLICATIONS

- Educational Market - General Purpose Instruction
- Industrial Sector - Fundamental R&D Measurement Applications

SPECIFICATIONS

		GDS-1054B	GDS-1072B	GDS-1074B	GDS-1102B	GDS-1104B	GDS-1202B
VERTICAL	Channels	4	2 + Ext	4	2 + Ext	4	2 + Ext
	Bandwidth	DC~50MHz(-3dB)	DC~70MHz(-3dB)	DC~70MHz(-3dB)	DC~100MHz(-3dB)	DC~100MHz(-3dB)	DC~200MHz(-3dB)
	Calculated Rise Time	7ns	5ns	5ns	3.5ns	3.5ns	1.75ns
	Bandwidth Limit	20MHz	20MHz	20MHz	20MHz	20MHz	20MHz
	Vertical Sensitivity Resolution	8 bit : 1mV~10V/div					
	Input Coupling	AC, DC, GND					
	Input Impedance	1M Ω // 16pF approx. ; GDS-1202B : 1M Ω // 14pF approx.					
	DC Gain Accuracy*	±3%					
	Polarity	Normal & Invert					
	Maximum Input Voltage	300Vrms, CAT I (300Vrms CAT II with GTP-070B- 4/100B-4, 200B-4 10:1 probe)					
	Offset Position Range	1mV/div : ±1.25V ; 2mV/div ~ 100mV/div : ±2.5V ; 200mV/div ~ 10V/div : ±125V					
	Waveform Signal Process	+,-, x, ÷, FFT, FFTrms, User Defined Expression ; FFT: 1Mpts; FFT: Spectral magnitude. Set FFT Vertical Scale to Linear RMS or dBV RMS ; FFT Window Display : Rectangular, Hamming, Handing, or Blackman-Harris					
TRIGGER	Source	CH1, CH2, CH3*, CH4*, Line, EXT** ; *four channel models only. ; **two channel models only					
	Trigger Mode	Auto (supports Roll Mode for 100 ms/div and slower), Normal, Single Sequence					
	Trigger Type	Edge, Pulse Width, Video, Pulse Runt, Rise & Fall, Timeout, Alternate, Event-Delay(1~65535 events), Time-Delay(Duration, 4nS~10S)					
	Holdoff range	4ns to 10s					
	Coupling	AC, DC, LF rej., Hf rej., Noise rej.					
	Sensitivity	1div					
EXTERNAL TRIGGER	Range	±2.5V					
	Sensitivity	DC ~ 100MHz Approx. 100mV ; 100MHz ~ 200MHz Approx. 150mV					
	Input Impedance	1M Ω ±3%~16pF					
HORIZONTAL	Time base Range	5ns/div ~ 100s/div (1-2.5 increments)					
	ROLL	100ms/div ~ 100s/div					
	Pre-trigger	10 div maximum					
	Post-trigger	2,000,000 div maximum					
	Timebase Accuracy	±50 ppm over any ≥1 ms time interval					
	Real Time Sample Rate	1GSa/s max.					
	Record Length	Max. 10Mpts					
	Acquisition Mode	Normal, Average, Peak Detect, Single					
	Peak Detection	2nS (typical)					
	Average	selectable from 2 to 256					
X-Y MODE	X-Axis Input	Channel 1; Channel 3*(four channel models only)					
	Y-Axis Input	Channel 2; Channel 4*(four channel models only)					
	Phase Shift	±3° at 100kHz					
CURSORS AND MEASUREMENT	Cursors	Amplitude, Time, Gating available; Unit : Seconds(s), Hz(1/s), Phase(degree), Ration(%)					
	Automatic Measurement	36 sets: Pk-Pk, Max, Min, Amplitude, High, Low, Mean, Cycle Mean, RMS, Cycle RMS, Area, Cycle Area, ROVShoot, FOVShoot, RPREShoot, FPRESHoot, Frequency, Period, RiseTime, FallTime, +Width, -Width, Duty Cycle, +Pulses, -Pulses, +Edges, -Edges, FRR, FRF, FFR, FFF, LRR, LRF, LFR, LFF, Phase					
	Cursors Measurement	Voltage difference between cursors (ΔV) Time ; difference between cursors (ΔT)					
	Auto Counter	6 digits, range from 2Hz minimum to the rated bandwidth					
CONTROL PANEL FUNCTION	Autoset	Single-button, automatic setup of all channels for vertical, horizontal and trigger systems, with undo Autoset					
	Save Setup	20set					
	Save Waveform	24set					
DISPLAY	TFT LCD Type	7" TFT WVGA color display					
	Display Resolution	800 horizontal x 480 vertical pixels (WVGA)					
	Interpolation	Sin(x)/x					
	Waveform Display	Dots, vectors, variable persistence (16ms~4s), infinite persistence					
	Waveform Update Rate	50,000 waveforms per second, maximum					
	Display Graticule	8 x 10 divisions					
	Display Mode	YT, XY					
INTERFACE	USB Port	USB 2.0 High-speed host port x1, USB High-speed 2.0 device port x1					
	Ethernet Port(LAN)	RJ-45 connector, 10/100Mbps with HP Auto-MDIX (Only for 4 channel models.)					
	Go-NoGo BNC	5V Max/10mA TTL open collector output					
	Kensington Style Lock	Rear-panel security slot connects to standard kensington-style lock					
POWER SOURCE		AC 100V ~ 240V , 50Hz ~ 60Hz , Auto selection , Power consumption: 30 Watts					
MISCELLANEOUS	Multi-Language Menu	Available					
	Operation Environment	Temperature : 0°C ~ 50°C. Relative Humidity ≤80% at 40°C or below; ≤ 45% at 41°C ~ 50°C					
	Online Help	Available					
DIMENSIONS & WEIGHT		380(W) x 208 (H) x 127.3(D)mm, Approx. 2.8kg					

The specifications apply when the GDS-1000B is powered on for at least 30 minutes under +20°C~+30°C .

Specifications subject to change without notice.

DS-1000BGD2DH

ORDERING INFORMATION

GDS-1202B	200MHz, 2 channels, Digital Storage Oscilloscope
GDS-1104B	100MHz, 4 channels, Digital Storage Oscilloscope
GDS-1102B	100MHz, 2 channels, Digital Storage Oscilloscope
GDS-1074B	70MHz, 4 channels, Digital Storage Oscilloscope
GDS-1072B	70MHz, 2 channels, Digital Storage Oscilloscope
GDS-1054B	50MHz, 4 channels, Digital Storage Oscilloscope

ACCESSORIES

User manual CD x 1, Power cord x 1
GTP-070B-4 : 70MHz(10:1/1:1) Switchable passive probe for GDS-1074B,GDS-1072B,GDS-1054B(one per channel)
GTP-100B-4 : 100MHz(10:1/1:1) Switchable passive probe for GDS-1104B, GDS-1102B(one per channel)
GTP-200B-4 : 200MHz(10:1/1:1) Switchable passive probe for GDS-1202B(one per channel)

OPTIONAL ASSESSORIES

GRA-426	Rack Adapter Panel	GCP-206P	Power supply for current probe (2 input channel)
GAk-003	50 Ω Impedance Adapter	GCP-425P	Power supply for current probe (4 input channel)
GSC-008	Soft Carrying Case	GTP-033A	Oscilloscope Probe, 35MHz
GTL-246	USB Cable, USB 2.0, A-B Type, 1200mm	GDP-025	1:1 Passive Probe, BNC(P/M)
GCP-300	300kHz/200A Current probe	GDP-025	25MHz High voltage differential probe
GCP-530	50MHz/30A Current probe	GDP-050	50MHz High voltage differential probe
GCP-500	500kHz/150A Current probe	GDP-100	100MHz High voltage differential probe
GCP-1030	100MHz/30A Current probe		
GCP-1000	1MHz/70A Current probe		

FREE DOWNLOAD

Software	OpenWave Software	Driver	USB Driver ; LabView Driver
-----------------	-------------------	---------------	-----------------------------

Global Headquarters

GOOD WILL INSTRUMENT CO., LTD.

T +886-2-2268-0389 F +886-2-2268-0639

China Subsidiary

GOOD WILL INSTRUMENT (SUZHOU) CO., LTD.

T +86-512-6661-7177 F +86-512-6661-7277

Malaysia Subsidiary

GOOD WILL INSTRUMENT (SEA) SDN. BHD.

T +604-6111122 F +604-6115225

Europe Subsidiary

GOOD WILL INSTRUMENT EURO B.V.

T +31 (0)40-2557790 F +31 (0)40-2541194

U.S.A. Subsidiary

INSTEK AMERICA CORP.

T +1-909-399-3535 F +1-909-399-0819

Japan Subsidiary

TEXIO TECHNOLOGY CORPORATION.

T +81-45-620-2305 F +81-45-534-7181

Korea Subsidiary

GOOD WILL INSTRUMENT KOREA CO., LTD.

T +82-2-3439-2205 F +82-2-3439-2207

India Subsidiary

GW INSTEK INDIA LLP.

T +91-80-6811-0600 F +91-80-6811-0626

GW INSTEK

Simply Reliable

Need to get repairs/service?

service@szmatrix.com

0086 755 2836 4276