



2400W PowerVerter Plus Industrial-Strength Inverter with 2 Outlets

MODEL NUMBER: PV2400FC



Highlights

- Designed for heavy duty and motor loads
- 24V DC input; 120V AC output; 2 outlets
- 2400W continuous output
- Peak surge output: OverPower (up to 1 hour)—3600W; Double-Boost (up to 10 seconds)—4800W
- High-efficiency power conversion
- · Automatic overload protection

Package Includes

- PV2400FC Inverter
- Instruction manual

Description

Continuously supplies up to 2400W of 120V AC power to 2 AC outlets from any 24V battery or automotive DC source. Frequency control locks AC output at 60Hz for operating stability of motor loads. Includes a set of high current DC input terminals for simple, permanent installation. Highly reliable large transformer design specializes in powering motors and other inductive loads with high-current startup needs. NOTE: To protect against high current draw that may occur during inverter failure, a fuse link rated at 250a should be positioned no more than 18" from the PV2400FC's battery in the positive line.

Features

- Converts 24V DC battery power to 120V AC power
- 2400W continuous output power
- Peak surge output: OverPower (up to 1 hour), 3600 watts; Double-Boost (up to 10 seconds), 4800W
- Set of 2 bolt-down DC wiring terminals for 24V battery connection; 2 x NEMA 5-15/20R outlets
- Frequency control for operating stability
- High-efficiency operation conserves batteries to prolong run time
- Diagnostic LEDs indicate load level (high, medium, and low) and battery charge (high, medium, and low)
- · DC fusing protects inverter against overload
- High-impact polycarbonate housing
- RJ45 port allows connection of APS/PowerVerter Remote Switch (APSRM4)

Specifications

OVERVIEW		
UPC Code	037332042200	
INPUT		
Maximum Input Amps / Watts	Full continuous load - 120A at 24V DC; No load - 2.2A at 24V DC	





Recommended Electrical Service	Requires 24V DC input source capable of delivering 120A for the required duration (when used at full capacity). For automotive applications, professional hardwire installation with 250A battery system fusing is recommended
Input Connection Type	Set of 2 bolt-down DC wiring terminals
Input Cord Length Details	User supplies cabling; 2/0 gauge or larger recommended
Voltage Compatibility (VDC)	24
ОИТРИТ	
Frequency Compatibility	60 Hz
Pure Sine Wave Output	No
Output (Watts)	2400
Nominal Output Voltage(s) Supported	120V
Output Receptacles	(2) 5-15R
Continuous Output Capacity (Watts)	2400
Peak Output Capacity (Watts)	4800
Output Voltage Regulation	Maintains PWM sine wave output voltage of 120 VAC (+/-5%)
Output Frequency Regulation	60 Hz (+/- 0.3 Hz)
Overland Destables	Circuit breaker
Overload Protection	Ground product
Overload Protection BATTERY	
	24
BATTERY	24
BATTERY DC System Voltage (VDC)	24
BATTERY DC System Voltage (VDC) USER INTERFACE, ALERTS & CON	TROLS Set of 6 LEDs provides continuous status information on load percentage (6 levels reported) and battery charge
BATTERY DC System Voltage (VDC) USER INTERFACE, ALERTS & CON Front Panel LEDs	TROLS Set of 6 LEDs provides continuous status information on load percentage (6 levels reported) and battery charge level (7 levels reported). See manual for sequences 3-position on/off/remote switch enables simple on/off power control plus "remote" setting that enables distant on/off control of the inverter system when used in conjunction with optional <a <a="" <="" class="productLink" conjunction="" control="" distant="" enables="" href="//tripoplite.eaton.com/Remote-Control-Module-Tripo-Lite-Power/Verter-Inverters-Inverter-" in="" inverter="" of="" off="" on="" optional="" remote"="" setting="" system="" td="" that="" the="" used="" when="" with="">
BATTERY DC System Voltage (VDC) USER INTERFACE, ALERTS & CON Front Panel LEDs Switches PHYSICAL	TROLS Set of 6 LEDs provides continuous status information on load percentage (6 levels reported) and battery charge level (7 levels reported). See manual for sequences 3-position on/off/remote switch enables simple on/off power control plus "remote" setting that enables distant on/off control of the inverter system when used in conjunction with optional APSRM4 > accessory
BATTERY DC System Voltage (VDC) USER INTERFACE, ALERTS & CON Front Panel LEDs Switches PHYSICAL Material of Construction	TROLS Set of 6 LEDs provides continuous status information on load percentage (6 levels reported) and battery charge level (7 levels reported). See manual for sequences 3-position on/off/remote switch enables simple on/off power control plus "remote" setting that enables distant on/off control of the inverter system when used in conjunction with optional -a class="productLink" href="/tripplite.eaton.com/Remote-Control-Module-Tripp-Lite-PowerVerter-Inverters-Inverter-Chargers~APSRM4">APSRM4 accessory Polycarbonate
BATTERY DC System Voltage (VDC) USER INTERFACE, ALERTS & CON Front Panel LEDs Switches PHYSICAL Material of Construction Cooling Method	TROLS Set of 6 LEDs provides continuous status information on load percentage (6 levels reported) and battery charge level (7 levels reported). See manual for sequences 3-position on/off/remote switch enables simple on/off power control plus "remote" setting that enables distant on/off control of the inverter system when used in conjunction with optional APSRM4 accessory Polycarbonate Fan Mounting slots enable permanent placement of inverter on any horizontal surface (see manual for additional
BATTERY DC System Voltage (VDC) USER INTERFACE, ALERTS & CON Front Panel LEDs Switches PHYSICAL Material of Construction Cooling Method Form Factors Supported	TROLS Set of 6 LEDs provides continuous status information on load percentage (6 levels reported) and battery charge level (7 levels reported). See manual for sequences 3-position on/off/remote switch enables simple on/off power control plus "remote" setting that enables distant on/off control of the inverter system when used in conjunction with optional -a class="productLink" href="l/tripplite.eacon.com/Remote-Control-Module-Tripp-Lite-PowerVerter-Inverters-Inverter-Chargers~APSRM4">APSRM4 accessory Polycarbonate Fan Mounting slots enable permanent placement of inverter on any horizontal surface (see manual for additional mounting information)
BATTERY DC System Voltage (VDC) USER INTERFACE, ALERTS & CON Front Panel LEDs Switches PHYSICAL Material of Construction Cooling Method Form Factors Supported Shipping Dimensions (hwd / in.)	TROLS Set of 6 LEDs provides continuous status information on load percentage (6 levels reported) and battery charge level (7 levels reported). See manual for sequences 3-position on/off/remote switch enables simple on/off power control plus "remote" setting that enables distant on/off control of the inverter system when used in conjunction with optional APSRM4 > accessory Polycarbonate Fan Mounting slots enable permanent placement of inverter on any horizontal surface (see manual for additional mounting information) 12.90 x 14.40 x 21.30
BATTERY DC System Voltage (VDC) USER INTERFACE, ALERTS & CON Front Panel LEDs Switches PHYSICAL Material of Construction Cooling Method Form Factors Supported Shipping Dimensions (hwd / in.) Shipping Dimensions (hwd / cm)	TROLS Set of 6 LEDs provides continuous status information on load percentage (6 levels reported) and battery charge level (7 levels reported). See manual for sequences 3-position on/off/remote switch enables simple on/off power control plus "remote" setting that enables distant on/off control of the inverter system when used in conjunction with optional APSRM4 accessory Polycarbonate Fan Mounting slots enable permanent placement of inverter on any horizontal surface (see manual for additional mounting information) 12.90 x 14.40 x 21.30 32.77 x 36.58 x 54.10
BATTERY DC System Voltage (VDC) USER INTERFACE, ALERTS & CON Front Panel LEDs Switches PHYSICAL Material of Construction Cooling Method Form Factors Supported Shipping Dimensions (hwd / in.) Shipping Dimensions (hwd / cm) Shipping Weight (lbs.)	TROLS Set of 6 LEDs provides continuous status information on load percentage (6 levels reported) and battery charge level (7 levels reported). See manual for sequences 3-position on/off/remote switch enables simple on/off power control plus "remote" setting that enables distant on/off control of the inverter system when used in conjunction with optional -ca class="product_ink" href="/tripplite.eaton.com/Remote-Control-Module-Tripp-Lite-PowerVerter-Inverters-Inverter-Chargers-APSRM4">APSRM4- accessory Polycarbonate Fan Mounting slots enable permanent placement of inverter on any horizontal surface (see manual for additional mounting information) 12.90 x 14.40 x 21.30 32.77 x 36.58 x 54.10 38.60





Unit Weight (lbs.)	39	
Unit Weight (kg)	17.69	
ENVIRONMENTAL		
Relative Humidity	0%-95% Non-Condensing	
STANDARDS & COMPLIANCE		
Product Compliance	RoHS	
WARRANTY & SUPPORT		
Product Warranty Period (Worldwide)	1-year limited warranty	

1000 Eaton Boulevard Cleveland, OH 44122 United States https://tripplite.eaton.com © 2025 Eaton. All Rights Reserved. Eaton is a registered trademark. All other trademarks are the property of their respective owners.